



Models				SH11000		SHT11500	
Type				R	D	R	S
Generator	Frequency (Hz)			50	60	50	60
	Type			2-pole, Field Rotating Type			
	Voltage Regulation System			AVR			
	Phase			Single		Three	
	AC Output	Rated Power (KVA)	50Hz	8.5	-	9.5	-
			60Hz	-	9.5	-	10.5
	Maximum Power (KVA)	50Hz	9.5	-	10.5	-	
		60Hz	-	10.5	-	11.5	
Rated Voltage (V)			220	120/240	220/380		
Rated Power Factor (cosφ)			1.0		0.8		
Engine	Maker			HONDA			
	Model			GX620			
	Displacement (CC)			614			
	Maximum Output (PS)			20(3,600rpm)			
	Ignition System			Transistor			
	Oil Alert System			YES			
	Starting System			Electric Starter			
Others	L X W X H (mm)			924 X 665 X 636 (804 with wheels)			
	Dry Weight (kg)	without wheel		159		160	
		with wheel		167		168	
	Fuel Tank Capacity (liters)			38			
	Sound Level [dB(A)/7m]	50Hz		74			
		60Hz					
Continuous Operating Hours (hr)	50Hz		7.0	-	7.0	-	
	60Hz		-	6.2	-	6.2	
Cooling System			Forced Air				
Engine Oil Refill Capacity (liters)			1.8 (with replace a filter) / 1.5 (without replace a filter)				