



Туре				SH3900EX
Generator	Frequency (Hz)			50, 60
	Туре			Self-Exciting, 2-pole, Field Rotating Type
	Voltage Regulation System			AVR
	Phase			Single
	AC Output	Rated Power (kVA)	50Hz	2.8
			60Hz	3.2
		Maximum Power (kVA)	ver 50Hz	3.3
			60Hz	3.9
		Rated Voltage (V)		220(R,S-type)
	DC Output (V-A)			12V-8.3A
	Rated Power Factor (cosφ)			1.0
Engine	Maker			HONDA
	Models			GX200
	Displacement (CC)			196
	Maximum Output (PS) 3,600rpm			6.5
	Ignition System			Transistor
	Oil Alert System			YES
	Starting System			Recoil
Others	L X W X H (mm)			623 × 43 × 491
	Dry Weight (kg)			46
	Fuel Tank Capacity (liters)			17
	[4D(A)/7]		50Hz	65
			60Hz	69
	Continuous Operating		50Hz	10
			60Hz	8.8